

Switchers

# HD 12-Channel Digital Video Switcher

**SE-3200****config**

|                                    |   |
|------------------------------------|---|
| Video Standard                     | Full HD   |
| Video Format                       | 1080p 50/59.94/60Hz<br>1080i 50/59.94/60Hz<br>720p 50/59.94/60Hz  |
| Video Processing                   | SDI: 4:2:2<br>HDMI: YUV 4:2:2, RGB: 4:4:4   |
| Input Routable / Crosspoint        | All 12, repeatable  |
| Video Input                        | 8x SDI, 4x HDMI   |
| Mix HD & SD Source                 | ----  |
| Computer Graphic Interface         | 4 via HDMI  |
| Video Output                       | 6x SDI Outputs assignable:<br>Multiview, PGM, PVW, PGM+DSK, Clean PGM, Clean PVW, Input 1-12, STILL 1, STILL 2, Flex source<br>3x HDMI assignable:<br>Multiview, PGM, PVW, PGM+DSK, Clean PGM, Clean PVW, Input 1-12, STILL 1, STILL 2, Flex source |
| Down-converted Output              | 1x SDI  |
| Built-in Multi-view Monitoring Out | HDMI & SDI assignable   |
| Analogue Audio Input               | 4x Balanced XLR   |
| Analogue Audio Output              | 2x Balanced XLR   |
| Digital Embedded Audio Support     | Input 2 channels, Output 4 channels   |
| Audio Delay Calibration            | Up to 16 fields or 8 frames per channel   |
| A+V Switching                      | Yes   |
| Chromakey                          | 4   |
| Title Creator                      | Yes, CG-200 software free download  |
| USK                                | 4x Keyer support Chromakey/ Linear/ Luma Key  |
| DSK                                | 2x DSK support Lumakey & Linear key (Key / Fill)  |
| Picture in Picture                 | 8 (4x PIP, 4x Flex Source)  |
| Logo Insertion                     | 2   |
| Still Store                        | 999+  |
| Effects                            | DVE, FTB, Cut, 32 Wipe with border  |
| Transition Preview                 | Full transitions preview  |
| Sync / Reference In/Out            | Built-in Genlock<br>Support external sync with loop thru  |
| Tally Output                       | 1x D-sub 25pin, dual color  |

|                       |  |
|-----------------------|--|
| PC Remote Control     | RS-232 / DVIP (Ethernet)   |
| Built-in Audio Mixer  | ----   |
| Special Features      | 4 User Memory Preset<br>Free Virtual Set and Stinger transition included   |
| Chassis               | 2 units, 2RU rack-mount mainframe  |
| Dimension (LxWxH)     | 433 x 312 x 76 mm (switcher)<br>432 x 252 x 88 mm (main unit)  |
| Weight                | 4 kg   |
| Power                 | DC 12V, 69W  |
| Operating Temp. Range | 0~40 °C  |
| What's in the Box     | 1 x SE-3200 Main Unit<br>1 x SE-3200 Control Board<br>2 x AD Switch DC 12V<br>1 x AC Cord<br>1 x DB9P TO DB9P Cable<br>12 x Screw<br>2 x 2U Ear Rack |