

## ATEM Microphone Converter



**US\$429**

Now it's easy to expand the MADI input on the ATEM Television Studio switchers to add multiple microphones or external audio mixer sources. The ATEM Microphone Converter simply plugs into the ATEM Television Studio MADI port, so there's no complex setup required and additional units can even be daisy chained for more sources. Each converter has 4 analog inputs that are mic/line selectable and have phantom power. The design features amazing audio quality with an extremely low noise floor, a wide dynamic range and very low distortion. The design even uses 8 separate ADCs on each separate input that work together to extend dynamic range! There is also an HDMI monitoring output with scrolling audio waveforms.

### Connections

#### Analog Audio Inputs

4 x Combination 3-pin XLR and TRS 1/4 inch Jack switchable between +24dB line and mic level with support for +48V phantom power.

#### MADI Inputs

1 x BNC supports 64 channel MADI digital audio

#### MADI Outputs

1 x BNC supports 64 channel MADI digital audio

#### HDMI Video Outputs

1 x monitor out.

#### Computer Interface

1 x USB-C with locking screw

#### Ethernet

Supports 10/100/1000 BASE-T.



---

## HDMI Output Standards

### HD Video Standards

1080p24, 1080p25, 1080p30,  
1080p48, 1080p50, 1080p60

### HDMI Monitoring

Displays ATEM Microphone Converter name and 4, 8, 12 or 16 audio channels with 60 second waveform history. Also includes individual channel name, VU meters, mic or line level setting and phantom power status.

---

## Audio

### ADCs Per Input

8

### Noise Floor

-129dBV

### Output Sample Depth

24-bit

### Digital Preamp

32-bit

### Total Harmonic Distortion at full scale

0.002%

### Output Sampling Rate

48KHz

### Dynamic Range

131dB(A)

### MADI Compliance

AES10-2020

---

## Software

### Software Control

Mac™ and Windows™ software upgrade via USB or Ethernet.

### Internal Software Upgrade

Via downloadable utility application.

---

## Operating Systems



Mac 12.0 Monterey,  
Mac 13.0 Ventura or later.



Windows 10, 64-bit.  
Windows 11.

---

## Settings Control

### Software Settings Control

USB and Ethernet via free software utility.

### Hardware Switches

Mini switches for selecting mic or line level and setting +48V phantom power on/off.

---

## Power Requirements

### Power Supply

1 x External 12V power supply with locking connector.

### Power Consumption

12W max.

### Operational Voltage Range

12V to 17.5V DC

---

## Physical Specifications



---

## Environmental Specifications

### Operating Temperature

0° to 40°C (32° to 104°F)

### Storage Temperature

-20° to 60°C (-4° to 140°F)

### Relative Humidity

0% to 90% non-condensing

---

## What's Included

ATEM Microphone Converter

External 12V DC power supply with locking connector and international socket adapters for most countries.

Welcome wallet with QR code for software download

---

## Warranty

3 Year Limited Manufacturer's Warranty.

Blackmagic Design Authorized Reseller